

- Always mount this unit safe and stable, and make sure the area will have proper ventilation. Take care this unit will not mounted in areas close to heat sources such as lighting fixtures, amplifiers, heat registers, stoves and radiators.
- Always contact us in case you have any doubts.

General Instructions

First familiarize yourself with the basic operation principals of this unit by reading the attached user manual carefully. These instructions contain important safety information regarding the use and maintenance of this unit.

Set Up

- Before plugging this unit to power make sure the voltage in your area matches the required voltage for the LED Wall Washer. All these units are available in 90/260V and 50/60Hz. please always make sure this unit voltage matches your area outlet voltage before attempting to operate the unit.
- There are two ways to control your professional LED Wall Washer. The first option is by 'stand alone' function, and probably the most used option by an external controller via DMX. DMX is the standard language allowing communication between controller and all kinds of DMX products from different manufacturers. The order in which fixtures are connected in a DMX line does not influence the DMX addressing. For example it does not matter if the last selected address is in the beginning or in the middle of a DMX line; the controller always will recognize the fixture by its address.

Product Instruction



JIA-J532

18*12W (4 in 1)

LED Wall Washer

JIA LIGHTIN

Display Operation

Addr	A001–A512	DMX512 address setting
CHnd	4CH	4channels setting
	8CH	8channels setting
	72CH	72channels setting
	76CH	76channels setting
SLnd	Auto	Host bootstrapping mode
	SL 1	DMX mode
	SL 2	Slave mode
SH**	0–20	Effect selection
Sped	0–100	Speed adjustment
r***	0–255	R Dimmer
G***	0–255	G Dimmer
b***	0–255	B Dimmer
W***	0–255	W Dimmer
LEd	OFF	Close lamp over 5sencods
	ON	Open

Unpacking

Thank you for purchasing the LED Wall Washer. Every LED Wall Washer has been well tested and has been shipped in perfect operating condition. When receiving our products carefully check the shipping carton for damage that might have happen during transport. In case of damage inspect the fixture for any damage or missing accessories necessary to operate. If parts are missing of fixture has been damaged please report this to us. Please do not take any action without first contacting us.

Introduction

The LED Wall Washer is part of a wider range DMX intelligent LED par lihgt. This lighting is compact and lightweight and very easy to use. It is ideal for any rental job or installation. The unit can be controlled by any DMX controller or in standalone mode.

Caution!

Do not attempt any repairs yourself! Doing so will void your manufactures warranty. In the unlikely event your unit may require service please contact

Warning!

To prevent or reduce the risk of electrical shock or fire, do not expose this unit to rain or any moisture.

Please read this user manual carefully to familiarize you with the basic operations of this unit.

Product Specifications

The professional LED Wall Washer is a RGBW color-mixing unit with 18 pieces of 12W 4in 1 LED. The lighting is available in 900V/60Hz and 240V/50Hz. With a power consumption of 125 watt and a LED lifetime rated between 60,000 and 100,000 hrs, it is a revolutionarily tool which suits in many applications. The unit comes complete with 100cm power cable including Schuko plug.

Safety Precautions

- Do not expose this unit to rain or other moisture.
- Before plugging to power be sure the local power outlet matches with the required voltage of the unit
- Do not remove the cover under any circumstances in case you're not qualified to do so.
- Never connect to power when cover is removed.
- Never use this unit if it becomes damaged
- Never connect this unit to any kind of dimmer and/or power-pack.
- If the unit will not be used for a long time, disconnect it from power supply.

4ch mode

ch	Function	Data
1	R Dimmer	0-255
2	G Dimmer	0-255
3	B Dimmer	0-255
4	W Dimmer	0-255

8CH mode	Function	Data
1	Dimmer	0-255
2	strobe	0-255
3	No-effect	0-15
	Self-walking mode	16-255
4	Speed adjustment	0-255
5	R Dimmer	0-255
6	G Dimmer	0-255
7	B Dimmer	0-255
8	W Dimmer	0-255

72CH mode

CH	Function	Data
1	1 R	0-255
2	1 G	0-255
3	1 B	0-255
4	1 W	0-255
.....		
5	2 R	0-255
6	2 G	0-255
7	2 B	0-255
8	2 W	0-255
.....		
69	18 R	0-255
70	18 G	0-255
71	18 B	0-255
72	18 W	0-255

76CH mode

CH	Function	Data
1	Dimmer	0-255
2	strobe	0-255
3	No-effect	0-15
	Self-walking mode	16-255
4	Speed adjustment	0-255
5	1 R	0-255
6	1 G	0-255
7	1 B	0-255
8	1 W	0-255
9	2 R	0-255
10	2 G	0-255
11	2 B	0-255
12	2 W	0-255
.....		
73	18 R	0-255
74	18 G	0-255
75	18 B	0-255
76	18 W	0-255