

# LED CO2 JET MACHINA

## USER MANUAL



Power: 200W

Control: DMX512 Control

LEDs: 12pcs \*3w RGB(3 in 1)

Spray Height: 6-8 Meters

Voltage: AC110/220V,50/60HZ

N.W.:6KG

G.W.:6.5KG

Size:30\*30\*42

The product has perfect performance and integrity packing. All users should be strictly comply with the warning and operating instructions as stated. Or we aren't in charge of any result by misusing. Any damage resulting by misuse is not within the company's warranty. Any fault or problem caused by neglecting the manual is also not in the charge of dealers.

### **Maintenance:**

1. To reduce the risk of electrical shock or fire, do not expose this unit to rain or moisture.
2. Always mount this unit in safe and stable matter.
3. Advise customer use controller to control the machine.
4. When you use the power control ,please make sure the CO2 spray ,each time don't more than 3 seconds.
5. After use, should pay attention to in the hose at the outlet of air ,don't let debris falling into the hose, so as to avoid the machine valve stuck.

### **DMX Channels:**

Channel 1:CO2 Spay(0-9)Off,(10-255)ON.

Channel 2:LED in red,(0-9)Off,(10-255)LED lights up gradually.

Channel 3:LED in green,(0-9)Off,(10-255)LED lights up gradually.

Channel 4:LED in blue, lights up gradually.

Channel 5:LED Strobe

Channel 6: Change the speed of LED's color automatically,(0-9)OFF,(10-2550 getting faster.

Channel 7:Change the speed of LED's color automatically,(0-9)OFF,(10-2550 getting faster.

Note:When channel 6 and channel 7 use together be 255, means control the sound ,but it can't control the CO2 spay .

### **Save Method:**

When the machine no CO2 spay

1. Please check the connector,if it have debris,clean it ,than use.
2. If the machine have sound ,please change the valve core.